

Assignment Quiz 3  
October 15, 2001

Instructor: B.L. Daku  
Time: 15 minutes  
Aids: None  
Name:  
Student Number:

$$\cos x = \frac{e^{ix} + e^{-ix}}{2}$$

$$\sin x = \frac{e^{ix} - e^{-ix}}{2j}$$

$$e^{ix} = \cos x + j \sin x$$

1. Consider an LTI system with frequency response

$$H(e^{j\omega}) = e^{-j(\omega/2 + \pi/4)}, \quad -\pi < \omega \leq \pi$$

Determine  $y[n]$ , the output of this system, if the input is

$$x[n] = \cos\left(\frac{15\pi n}{4} - \frac{\pi}{3}\right)$$

for all  $n$ .

$$H(e^{j\omega}) = e^{-j(\frac{\omega}{2} + \frac{\pi}{4})}$$

$$x[n] = \cos\left(\frac{15\pi n}{4} - \frac{\pi}{3}\right)$$

$$= \frac{1}{2} \left( e^{j(\frac{15\pi n}{4} - \frac{\pi}{3})} + e^{-j(\frac{15\pi n}{4} - \frac{\pi}{3})} \right)$$

$$= \frac{1}{2} \left( e^{j(\frac{15\pi n}{4} + \frac{\pi}{3})} + e^{j(\frac{15\pi n}{4} - \frac{\pi}{3})} \right)$$

$$y_1[n] = \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{8} + \frac{\pi}{8})} e^{j(\frac{15\pi n}{4} + \frac{\pi}{3})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{8} - \frac{\pi}{24})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{35\pi n}{24})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{24} - \frac{9\pi n}{24})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{24} + \frac{9\pi n}{24})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{24\pi n}{24})} \right]$$

$$= \frac{1}{2} \left[ e^{-j\pi n} \right]$$

$$y_2[n] = \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{8} + \frac{\pi}{8})} e^{j(\frac{15\pi n}{4} - \frac{\pi}{3})} \right]$$

$$= \frac{1}{2} \left[ e^{-j(\frac{15\pi n}{8} - \frac{\pi}{24})} \right]$$

$$= \frac{1}{2} e^{-j\frac{35\pi n}{24}} \left[ \cos\left(\frac{15\pi n}{24} - \frac{6\pi n}{24}\right) \right]$$

$$y[n] = e^{-j\frac{5\pi n}{24}} \left( \cos\left(\frac{\pi n}{4}\right) \right)$$

$$\frac{8\pi}{4} = 2\pi$$

$$\frac{15\pi}{4} = \frac{7\pi}{4} - \frac{\pi}{4}$$

$$\omega = -\frac{\pi}{4}$$

Assignment Quiz 4  
October 29, 2001

Instructor: B.L. Daku  
Time: 15 minutes  
Aids: None  
Name:  
Student Number:

$$e^{ix} = \cos x + j \sin x$$

1. The impulse response for an LTI system is given by

$$h[n] = e^{j\pi/4} \delta[n-2]$$

- (a) Determine the frequency response,  $H(e^{j\omega})$ , for the system.  
(b) Determine the output  $y[n]$  given the input

$$x[n] = 2 + 4 \cos\left(\frac{\pi n}{2} - \frac{3\pi}{10}\right)$$

Simplify  $y[n]$ , making it a function of a cosine.

$$H(e^{j\omega}) = \sum_{k=-\infty}^{\infty} h[k] e^{-j\omega k}$$

$$= e^{j\frac{\pi}{4}} e^{-j\omega \cdot 2}$$

$$= e^{j(\frac{\pi}{4} - 2\omega)}$$

$$y[n] = H(e^{j\omega}) x[n]$$


$$x[n] = 2 + 2 \left[ e^{j(\frac{\pi n}{2} - \frac{3\pi}{10})} + e^{-j(\frac{\pi n}{2} - \frac{3\pi}{10})} \right]$$

$$y[n] = 2 \left( e^{j(\frac{\pi}{4} - 2 \cdot 0)} \right) + 2 \left[ e^{j(\frac{\pi}{4} - 2 \cdot \frac{\pi}{2})} e^{j(\frac{\pi n}{2} - \frac{3\pi}{10})} + e^{j(\frac{\pi}{4} - 2 \cdot \frac{\pi}{2})} e^{-j(\frac{\pi n}{2} - \frac{3\pi}{10})} \right]$$

$$= 2 e^{j\frac{\pi}{4}} + 2 \left[ e^{-j(\frac{\pi}{4} - \frac{3\pi}{10})} e^{j(\frac{\pi n}{2} - \frac{3\pi}{10})} + e^{-j(\frac{\pi}{4} - \frac{3\pi}{10})} e^{-j(\frac{\pi n}{2} - \frac{3\pi}{10})} \right]$$

$$= 2 e^{j\frac{\pi}{4}} + 2 \left[ e^{j(\frac{\pi n}{2} - \frac{3\pi}{10})} + e^{-j(\frac{\pi n}{2} - \frac{3\pi}{10})} \right]$$

$$= 2 e^{j\frac{\pi}{4}} + 4 \left( \cos\left(\frac{\pi n}{2} - \frac{3\pi}{10}\right) \right) e^{j\frac{\pi}{4}}$$



2 is a constant  
DC term  
 $\omega = 0$

$$\frac{3\pi}{10} - \frac{3\pi}{4}$$

$$\frac{12\pi}{40} - \frac{30\pi}{40}$$